

SANGEAN

A WORLD OF LISTENING



digitalradioplus.com.au

WFR-1D+

Stereo Digital Radio
Receiver



\$699.00 RRP

AUD\$ inclusive of GST

WFR-1D+ Internet Radio / Network Music Player / DAB+ / FM-RDS / Stereo Digital Radio Receiver

- **Internet Radio** – listen to the world in your home
- **Network Music Player** – plays the music stored on your computer
- **FM and DAB+/ Digital Radio Plus**
- Instant access to over 16,000 internet radio stations
- Search by Country, Genre and Favourite stations
- Real Audio, MP3, AAC+, and WMA compatible
- Fully upgradeable software
- Superior reception and sound quality
- High gloss wooden cabinet with stereo speakers
- FM-RDS displays station name and/or song title
- Auxiliary In / Line Out
- **Wi-Fi and Ethernet** connection
- F-type antenna connection (under telescopic rod)
- Remote Control

See over page for technical specifications.

CANOHM

3/200 Turner Street
Port Melbourne Victoria 3207

Telephone 03 9645 4700
Facsimile 03 9646 7366

Email sales@canohm.com.au
www.sangean.com.au

ABN 57 004 817 949

May 2009

| | | MODEL | WFR-1D+ |
|---------------------|------------------------|-----------------------------|------------------------|
| TUNER | DAB+ | | Band III (5A - 13F) |
| | FM | Frequency MHz | 87.5 - 108 |
| | | Stereo | Earphones / Speaker |
| | | RDS/RBDS | PS/PTY/RT |
| | WiFi | IEEE 802.11 b/g (GHz) | 2.4 - 2.4835 |
| | Ethernet | IEEE 802.3 | Yes |
| | | Internet Radio (iRadio) | vTuner |
| | Media Player (mPlayer) | Yes | |
| | Presets | | 20 (10 + 10) |
| MEDIA | CD | CD / CDR / CDRW | No |
| | SD | | No |
| | USB | | No |
| | Aux-in | | Yes |
| CLOCK | Real time | Radio control - DAB/iRadio | iRadio |
| | Alarm | Tuner / Media / Buzzer | Tuner / Media / Buzzer |
| | Sleep | | Yes |
| | Snooze | | Yes |
| DISPLAY | | LCD / VFD | LCD |
| | | View area (mm) | 59 x 33.5 |
| | | Graphic / Character type | Graphic 128 x 64 |
| | | Back light | Yes |
| FEATURES | | Record - SD / Flash | No |
| | | Rewind - SDRAM | No |
| | | Program upgrade | Via USB-B / Internet |
| AUDIO | EQ | Treble / Bass control | Yes |
| | | EQ (Sound effect selection) | 6 |
| AMPLIFIER | | Speaker output (TYP) | 5W + 5W |
| | | Earphones output | 5 + 5 mW |
| SPEAKERS | | Size | 3 inches x 2 |
| | | Impedance | 8 ohms |
| | | Magnetically shielded | Yes |
| I/O SOCKETS | | AC/DC - in | AC |
| | | Aux - in | Yes |
| | | Line - out | Yes |
| | | Digital - out | No |
| | | Earphones | Yes |
| | | SD | No |
| | | USB | USB-B |
| | | Ext. Antenna | WiFi, FM |
| | | RJ - 45 | Yes |
| | | | |
| POWER SUPPLY | | AC | Yes |
| ACCESSORIES | | AC cord | Yes |
| | | Remote control | Yes |
| | | Ext. Antenna | WiFi, FM |
| | | CAT5E cable (Ethernet) 3m | Yes |
| | | | |
| DIMENSIONS | | W x H x D (mm) | 326 x 108 x 210 |
| | | Weight (g) | 2946 |

E&OE

WFR-1D+

Stereo Digital Radio Receiver

