

SANGEAN

A World of Listening

ATS-818

WORLD RECEIVER



\$349.00 RRP

AUD\$ inclusive of GST

- * Professional digital multi-band world receiver.
- * Continuous AM coverage 150-29999 kHz + FM 87.5-108 MHz.
- * Five tuning methods-direct frequency tuning, auto scan, manual scan, memory recall and conventional rotary tuning.
- * 54 memory presets-9 presets each on LW/MW bands and 18 presets each on SW/FW bands.
- * FM stereo via earphones.
- * Dual time display for UTC and local time.
- * Signal strength and battery strength indicator.
- * AM wide/narrow filter.
- * Adjustable Sleep Timer.
- * Full coverage SW meter band from 120 m to 11 m.
- * High/Low tonecontrol and safety lock switch.
- * Standby function to turn on radio or buzzer at pre-programmed time.
- * Adjustable RF GAIN prevents overloading from stronger stations.
- * BFO control (Beat Frequency Oscillator) enables reception of SSB (Single Side Band) and CW (Morse Code) transmissions.
- * Dual conversion design.
- * Standby recording function provides recording at pre-programmed time.
- * Play, record LED indicator.
- * Auto stop on tape playing.
- * Normal/CrO2 tape selection.

See over page for technical specifications.

CANOHM

3/200 Turner Street Port Melbourne VIC 3207
 Ph: 03 9645 4700 * Fx: 03 9646 7366 * Email: sales@canohm.com.au
 Website: www.canohm.com.au

SANGEAN



► MODEL

ATS-818

TUNING	Type	PLL synthesizer
	Memory Presets	54
	Rotary Tuning	Yes
	Auto Tuning System	
DISPLAY	10-Key input	Yes
	Type	LCD
	Size (mm)	58 x 26
BAND FM	Back light	Yes
	Frequency MHz	87.5-108/76-108
	Stereo (Via Headphone)	Yes
LW	RDS	
	Frequency kHz	153-279
	MW	Frequency kHz
SW	Frequency MHz	1.711-29.999
	Meter bands	120,90,75,60,49,41,31,25,21,19,16,13,11
	AM	SSB SSB
CLOCK	Dual conversion	Yes
	Wide/Narrow	Yes
	Real time	Yes
	Dual/World time	Dual time
	Alarm Radio	Yes
	Alarm Buzzer	HWS
	Snooze	
Sleep	Yes	
CASSETTE	Radio control	
	Play	Yes
AUDIO OUTPUT	Recordable	Yes
	Tone control	Yes (Rotary)
OUTPUT POWER BY	Speaker unit	3 inch 4 ohm
	Buzzer	
POWER SUPPLY	AC/DC IN (Speaker)	
	Batteries (Speaker)	700 mW
	Earphones	5+5 mW
I/O SOCKET	DC IN	6 V DC 400 mA
	Batteries (Main power)	4 x 1.5 V (UM-1)
	Batteries (Back up)	3 x 1.5 V (UM-3)
ACCESSORIES	DC in	Yes
	AC in	
	Earphones	Yes
	Line out	
	Ext. Antenna	AM
DIMENSIONS	AC Adapter	Yes
	WxHxD (mm)	296 x 192 x 68
	Weight (g)	2000 (without batteries)