

SANGEAN

A World of Listening

ATS-909

WORLD RECEIVER



\$499.00 RRP

AUD\$ inclusive of GST

- ★ Professional digital multiband world receiver.
- ★ 307 memories (216 in SW, 18 each in MW/FM, 9 in LW plus priority station)
- ★ Five Tuning methods-direct frequency tuning, auto scan, manual tuning, memory recall and rotary tuning.
- ★ ATS (auto tuning system)-auto scan and preset in priority of signal strength in FM/MW/LW bands.
- ★ EE PROM for memories back up.
- ★ FM stereo via earphones.
- ★ 29 pages SW station memory, 9 memories in every page.
- ★ Automatic search strongest signal station within SW station pages.
- ★ 8 characters for editing station name in display.
- ★ SSB (USB/LSB) 40Hz/step on fine tuning.
- ★ AM RF gain control.
- ★ Built-in 42 world cities time plus D.S.T. device.
- ★ 3 individual timers.
- ★ Adjustable sleep timer.
- ★ Alarmed by radio or HWS(Humane Wake System) buzzer.
- ★ Battery and signal strength indicator.
- ★ Tone control (Music/Normal/news).
- ★ Direct key to recall favourite station in one button.
- ★ Dual conversion device.
- ★ REC out and standby control output.
- ★ Pre-programmed station name and frequency according to customer's requirement before ex-factory.
- ★ AM wide/narrow filter and FM mono/stereo selector.
- ★ RDS (Radio Data System) displays station name and clock time.

See over page for technical specifications.

CANOHM

3/200 Turner Street Port Melbourne VIC 3207
 Ph: 03 9645 4700 ★ Fx: 03 9646 7366 ★ Email: sales@canohm.com.au
 Website: www.canohm.com.au

SANGEAN



► MODEL

ATS-909

TUNING	Type	PLL synthesizer
	Memory Presets	306
	Rotary Tuning	Yes
	Auto Tuning System	Yes
DISPLAY	10-Key input	Yes
	Type	LCD
	Size (mm)	82 x 42
BAND FM	Back light	Yes
	Frequency MHz	87.5-108/76-108
	Stereo (Via Headphone)	Yes
	RDS	PS,PI,CT
LW	Frequency kHz	153-519
MW	Frequency kHz	520-1710
SW	Frequency MHz	1.711-29.999
	Meter bands	120,90,75,60,49,41,31,25,21,19,16,15,13,11
AM	SSB	USB/LSB
	Dual conversion	Yes
	Wide/Narrow	Yes
CLOCK	Real time	Yes
	Dual/World time	World time
	Alarm Radio	Yes
	Alarm Buzzer	HWS
	Snooze	Yes
	Sleep	Yes
	Radio control	RDS-CT
AUDIO OUTPUT	Tone control	Yes (Slide)
	Speaker unit	3 inch 8 ohm
	Buzzer	Yes
OUTPUT POWER BY	AC/DC IN (Speaker)	300 mW
	Batteries (Speaker)	5+5 mW
	Earphones	
POWER SUPPLY	DC IN	6 V DC 400 mA
	Batteries (Main power)	4 x 1.5 V (UM-3)
I/O SOCKET	DC in	Yes
	AC in	
	Earphones	Yes
	Line out	Yes
	Ext. Antenna	AM
ACCESSORIES	AC Adapter	Yes
	Carrying pouch	Yes
	Earphones	Yes
	SW antenna	Yes
DIMENSIONS	WxHxD (mm)	215 x 135 x 37.5
	Weight (g)	718