

SANGEAN

A World of Listening

PR-D4

FM / AM DIGITAL TUNING
PORTABLE RECEIVER



\$169.00 RRP

\$149.00 with AC adaptor

AUD\$ inclusive of GST

- * PLL Synthesized tuning system.
- * 10 memory presets (FM5, AM5).
- * Rotary volume control.
- * LCD displays separately clock and radio information.
- * Auto scan stations.
- * Two alarm timers (radio and buzzer).
- * Snooze.
- * Sleep (auto shut off).
- * Battery power status indication.
- * 3 inches full range speaker.
- * Long lasting battery operation.
- * DC 6 V jack.
- * Headphones jack.

See over page for technical specifications.

CANOHM

3/200 Turner Street Port Melbourne VIC 3207

Ph: 03 9645 4700 * Fx: 03 9646 7366 * Email: sales@canohm.com.au

Website: www.canohm.com.au

SANGEAN



► MODEL

PR-D4

TUNING	Type	PLL synthesizer
	Memory Presets	10 / 15 (Option)
	Rotary Tuning	
	Auto Tuning System	
DISPLAY	Type	LCD
	Size (mm)	99.6 x 24.6
	Back light	Yes
BAND FM	Frequency MHz	87.5-108 / 76-90 CH1,2,3
	Stereo	
	RDS	
MW	Frequency kHz	520-1710 / 522-1629
CLOCK	Real time	Yes
	Alarm Radio	Yes
	Alarm Buzzer	HWS
	Snooze	Yes
	Sleep	Yes
OUTPUT	Speaker unit	3 inch 4 ohm
	Buzzer	
OUTPUT POWER BY	AC/DC IN (Speaker)	
	Batteries (Speaker)	700 mW
	Earphones	5+5 mW
POWER SUPPLY	DC IN	6 V DC 400 mA
	Batteries (Main power)	4 x 1.5 V (UM-1)
I/O SOCKET	DC in	Yes
	AC in	
	Earphones	Yes
ACCESSORIES	AC Adapter	Yes (with PR-D4AD version)
DIMENSIONS	WxHxD (mm)	237 x 148 x 62
	Weight (g)	840