

SANGEAN

PR-D18



FM-Stereo / AM Digital Tuning Portable Receiver

- 10 station presets (5 FM, 5 AM)
- Easy to read LCD display with backlight
- Auto station seek
- Clock
- 2 alarm timers - radio or buzzer
- HWS (Humane Wake System) buzzer
- Adjustable sleep timer
- Snooze function
- Battery power status indication
- Lock switch
- I/O jacks: DC in and headphone
- Available in White with Royal Blue trim

E&OE

See over page for technical specifications.

CANOHM

4/30 Prohasky Street,
Port Melbourne Victoria 3207

Telephone 03 9644 7888
Facsimile 03 9646 7366

Email
sales@canohm.com.au

www.sangean.com.au
www.canohm.com.au

ABN 57 004 817 949
November 2016



SANGEAN

SPECIFICATIONS

Tuning	Type	DSP Tuner	
	Memory Presets	10 (5 FM and 5 AM)	
Display	Dial Scale	LCD	
	View Area mm	51 x 14.5	
	Graphic / Character Type	Segment	
	Back Light	Yes	
Feature	Stereo	Via Earphones	
Tuner	FM	Frequency (MHz)	87.5 - 108 KHz
	AM	Frequency (kHz)	522 - 1710
Clock	Real Time	Yes	
	Radio Alarm	Yes	
	Buzzer Alarm	HWS	
	Adjustable Alarm Level	Buzzer Alarm	
	Snooze	Yes	
	Sleep	Yes	
Output Devices Speaker	Size	57mm	
	Impedance	8 ohms	
	Magnetically Shielded	Yes	
Output Power (Typical)	AC / DC in (Speaker)	1W	
	Batteries (Speaker)	1W	
	Earphones	1.5 + 1.5 mW	
Power Supply	DC in	6V DC 400mA	
	Batteries (Main Power)	4 x 1.5V (AA)	
I/O Socket	DC in	Yes	
	Earphones	Yes 3.5mm	
Dimensions	W x H x D (mm)	166 x 108 x 38	
	Weight (g)	400	
Warranty		12 months	

PR-D18

