

SANGEAN

Digital
Radio

DPR-67



DAB+ / FM-RDS Digital Radio Receiver

- 10 station presets (5 DAB+, 5 FM)
- Information display for service data
- Manual / Search tuning
- Menu - selection of major functions
- Easy to read LCD display with backlight
- Automatic station search
- Clock
- Lock switch - avoids accidental operation
- Plays on rechargeable and dry-cell batteries
- Rechargeable battery facility with charging LED indicator
- USB B type socket for software update
- Available in other colours



E&OE

See over page for technical specifications.

CANOHM

4/30 Prohasky Street,
Port Melbourne Victoria 3207

Telephone 03 9644 7888
Facsimile 03 9646 7366

Email
sales@canohm.com.au

www.sangean.com.au
www.canohm.com.au

ABN 57 004 817 949
November 2016

SPECIFICATIONS

Tuner	DAB	Band III Frequency (MHz)	174 - 240 (W / DAB+)
	FM	Frequency (MHz)	87.5 - 108
		RDS	PS / PTY / CT / RT
	Preset		10 (5 DAB+ and 5 FM)
Clock	Real time	Radio Control - DAB / RDS	DAB / RDS
Display		LCD / VFD	LCD
		View Area (mm)	51 x 14.5
		Graphic / Character Type	16 characters on 2 Lines
		Back Light	Yes
Feature		Stereo	Via Earphones (not supplied)
		Charger	Yes
		Software Upgrade	Via USB - B
		Other	Lock button
Amplifier		Speaker Output	0.5 W
		Earphones Output	5 + 5 mW
		Others	Class D amplifier
Speaker		Size	2 1/4 inches
		Impedance	8 ohms
		Magnetically Shielded	Yes
Colour Options			Blue
			Grey
			Red
I/O Socket		AC / DC - in	DC
		Earphones	Yes
		USB	USB - B (for Software Upgrade)
Power Supply		DC	7.5V / 0.8A
		Batteries	4 x 1.5V (UM- 3) AA-Size
Accessories		AC Adapter	7.5V / 0.8A
Dimensions		W x H x D (mm)	166.2 x 108.3 x 37.8
		Weight (g)	400
Warranty			12 months

DPR-67

